



KOP100

Programmable battery charger

MAIN FEATURES

- For Lead-acid, NiZn, NiCd, NiMH and lithium batteries
- Fully automatic operation
- Completely programmable
- Up to five charging phases
- Simple to use and program
- Battery monitor and Ah counter
- High precision
- Battery status LED indicators
- Fanless / Compact size
- Battery temperature compensation
- Exceeds the requirements of the Energy Star 2.0



TECHNICAL CHARACTERISTICS

■ Nominal battery voltage	12V	24V
■ Max. output voltage	17V	34V
■ Nominal output current	8A	4A
■ Efficiency	87%	89%
■ Peak input current	1,1A	
■ Input voltage	230V ±15% 50-60Hz	
■ Dimensions (L x W x H)	110 x 156 x 60mm	
■ Weight	1,3kg	

www.piktronik.com

